

2.3 inch Six-Digit

Countdown timer with top mounted controls

[DC-256T-DN](#)

DC-Digital
tm



Features

- Counts down from 99 hrs to hundredths of a second
- Heavy duty extruded aluminum enclosure
- Displays up to 100ths of a sec
- 1 year Warranty
- Made in the USA
- Top mounted tactile pushbutton controls
- Large 2.3 Inch Super Bright Bar LED's
- Factory serviceable modular design
- Visible up to 120Ft.

Options

- RF Wireless controls
- BCD Rotary Set Switches
- Input redundancy, terminal block and switches
- 2-Wire Power and Data
- 100s of options call 800-977-6872

Specifications

- **Input** Tactile momentary pushbuttons mounted on the top of the enclosure (1) Start-Stop (pause), (1) Reset to the set value, (1) Reset to zero, (1) Set Hours, (1) Set Minutes
- **Display** 2.3 Inch, Six digit, Seven Segment, Red LED display
- **Case** Extruded Aluminum; 12.875"W x 5.75"H x 2.25"D
- **Weight** 7.0 Pounds
- **Power Source** 5 Watts; 90 – 240VAC 50/60 Hz (12VDC @ 700 ma power supply, [PS-12-700](#))
- **Operating Temp** 0° to 49° Celsius (32° to 120° Fahrenheit)
- **Case Finish** Tough, Finger Print Resistant, Black Powder Coating
- **Cabling** (2) 22 gauge 12 Inch (white and green) pigtails wiring out of the back of the enclosure

[DC-256T-DN](#) Description

The DC-Digital [DC-256T-DN](#) is designed to be used where a highly visible countdown timer is needed. The [DC-256T-DN](#) utilizes the **shift digit technology** that allows the user to see hours as well as hundredths of a second. The flexibility of this unique design gives it a broad range of applications in industry, government, schools and churches. The [DC-256T-DN](#), countdown timer comes with an extruded aluminum case, polycarbonate lens, and keyhole mounting brackets. This equipment is proudly made in the USA. This display is factory serviceable.

DC-256T-DN mounting and Dimensions

There are (2) adjustable teardrop tabs for mounting the [DC-256T-DN](#) to a wall. Note: The teardrop mounting tabs adjust wider or narrower by loosening their respective set screw and sliding it along the enclosure channel.

